

Bundled Cable Specifications					
Part Number (Stock Code)	LMR-BC-200-FR-6-OS (31834)	LMR-BC-400-4 (31832)	LMR-BC-400-7 (31836)	LMR-BC-400-9 (31831)	LMR-BC-400-9-LW (31833)
Components	LMR-200-FR	LMR-400	LMR-400	LMR-400	LMR-LW400
Bundle Configuration	F-6	F-4	1-6	1-8	1-8
Outer Protection	Braid & FR Jacket	Jacket	Jacket	Jacket	Jacket
Overall Diameter (in)	.709	1.060	1.350	1.575	1.575
Weight (lbs/ft)	.25	.37	.63	.75	.67
Bend Radius (in)	7	10	14	16	16
Temperature Range	-40°F to + 185°F (-40°C to + 85°C)				
Impedance	50 Ohms				

Install Tools

The LMR bundled cable tool package contains a number of unique products designed for easy use and long life. The ST-BC-1 and ST-BC-2 make up a universal outer sheath removal tool set that can be used with any of our bundled cables. If working with the BC400-7 and BC400-9, the GST-BC400-7 and GST-BC400-9 respectively are the best value, both economically and for ease of use.

The GST-400A easily accomplishes the otherwise challenging task of removing the inner cable's outer jacket from the BC400 bundled cables series. This tool is only needed when installing ground features.



GST-BC400-9:
Custom designed to quickly remove the outer sheath of the BC400-9 cable.



ST-BC-2:
Can be used in combination with the ST-BC-1 to remove the outer sheath of a bundled cable for grounding or fan out.



ST-BC-1:
Can be used in combination with the ST-BC-2 to remove the outer sheath of a bundled cable for grounding or fan out.



GST-400A:
Custom designed to quickly remove the outer jacket of the individual internal cables of LMR-400 based bundled cables.